

K-Shear Accelerometers

Type 8702B..., 8704B...

General purpose, voltage mode accelerometers

Small, relatively light weight general purpose accelerometers for vibration measurements in wide range of applications. Available in three measuring ranges 25 g, 50 g and 100 g, all range types are available in a ground isolated option. These accelerometers feature a rugged, hermetically sealed construction.

- Low impedance, voltage mode
- · Quartz-shear sensing elements
- Ultra-low base strain
- Minimal thermal transient response
- Lightweight, hermetically sealed Titanium case
- Conforming to CE

Description

The Type 8702B... side connector and 8704B... top connector accelerometer series use a unique shear mode sensing element made of stable quartz crystals. The quartz sensing elements afford excellent long-term stability that ensure repeatable, accurate measurements for many years. Additionally the shear element design provides low transverse sensitivity along with an insensitivity to base strain and thermal transients.

All units are hermetically sealed and are constructed entirely of titanium or a combination of titanium and stainless steel. An internal circuit Piezotron impedance converter provides a high signal level at low impedance output.


Models identified with an M1 are ground isolated versions. All units are hermetically sealed and are constructed entirely of titanium or a combination of titanium and stainless steel.


Application


All types are designed for general purpose vibration measurement in a laboratory or industrial environment. They can be used for environmental testing (with or without temperature cycling), ESS, vehicle tests, automotive NVH testing, rotating machinery vibration analysis.

Accessing TEDS data

Accelerometers with a "T" suffix are variants of the standard version incorporating the "Smart Sensor" design. Viewing an accelerometer's data sheet requires an Interface/Coupler such as Kistler's Type 5165A... or 5000M04 with TEDS Editor software. The Interface provides negative current excitation (reverse polarity) altering the operating mode of the PiezoSmart sensor allowing the program editor software to read or add information contained in the memory chip.









Dimensions are shown in [in], unless otherwise note





Technical data

Specification	Unit	Type 8702/4B25	Type 8702/4B50	Type 8702/4B100
Acceleration range	g	±25	±50	±100
Acceleration limit	gpk	±50	±100	±200
Transverse acceleration limit	gpk	±50	±100	±200
Threshold nom.	grms	0.002	0.004	0.006
Sensitivity, ±5 %	mV/g	200	100	50
Resonant frequency mounted nom.	kHz	54	54	54
Frequency response, ±5 %	Hz	1 8,000	0.5 10,000	0.5 10,000
Amplitude non-linearity	%FSO	±1	±1	±1
Time constant nom.	S	1	2	1.5
Transverse sensitivity nom., (max. 3)	%	1.5	1.5	1.5
Long term stability	%	±1	±1	±1
Environmental				
Base strain sensitivity @ 250 με	g/με	0.01	0.01	0.01
Shock limit (1 ms pulse)	gpk	2,000	2,000	2,000
Temperature coeff. of sensitivity	%/°F	-0.03	-0.03	-0.03
Operating temperature range	°F	-65 210	-65 210	-65 210
Storage temperature range	°F	-100 250	-100 250	-100 250
Output	<u> </u>			
Bias nom.	VDC	11	11	11
Impedance	Ω	<100	<100	<100
Voltage full scale	V	±5	±5	±5
Current	mA	2	2	2
Source			1	1
Voltage	VDC	20 30	20 30	20 30
Constant current	mA .	4	4	4
Impedance min.	kΩ	100	100	100
Construction				
Sensing element	type	quartz-shear	quartz-shear	quartz-shear
Housing/base	material	Titanium/St. Stl.	Titanium/St. Stl.	Titanium/St. Stl.
Degree of protection case/connector	type	hermetic	hermetic	hermetic
Connector				
Ground isolated	type	10-32 neg.	10-32 neg.	10-32 neg.
		with pad/M1	with pad/M1	with pad/M1
Mass	grams	8.7/7.5	8.7/7.5	8.7/7.5
M1	grams	9.7/8	9.7/8	9.7/8
Mounting (10-32 thd.x0.13 dp)	type	stud	stud	stud
Mounting torque	lbf-in	18	18	18

¹ g = 9.80665 m/s^2 , 1 inch = 25.4 mm, 1 gram = 0.03527 oz, 1 lbf-in = $0.1129 \text{ N} \cdot \text{m}$



measure analyze innovate.

Type 870 □□□□

Mounting

A threaded 10-32 UNF stud provides positive attachment of the accelerometer to the test structure. Reliable and accurate measurements require that the mounting surface be clean and flat.

The instruction manual for the Type 8702B... and 8704B... series accelerometers provides detailed information regarding mounting surface preparation.

Included accessories	Туре
 10-32 mounting stud 	8402
 10-32 to M6 mounting stud 	8411

Optional accessories	Туре
 Mounting magnet 	8452A
 Triaxial mounting cube 	8502
 Adhesive mounting base 	8436

Ordering key

Format (Field 14 Geometry = 0)

LMS Template 118, Aerospace

Format (Field 14 Geometry = 1) P1451.4 v1.0 template 25 –

Transfe Function Disabled P1451.4 v1.0 template 25 –

Transfer Function Enabled

Connector location		^ ^ ^
Side connector	2B	
Top connector	4B	
Measuring range		
±25 g	25	
±50 g	50]
±100 g	100]
Variant		
Standard		
Ground isolated	M1	
TEDS templates		
Default, IEEE 1451.4 V0.9	Т	
Template 0 (UTID 1)		
IEEE 1451.4 V0.9 Template 24	T01	1
(UTID 116225)		
LMS Template 117,	T02	
Free format Point ID		
LMS Template 118, Automotive	T03	

T04

T05

T06

Measuring chain					Туре
1	1 Low impedance sensor				8702/04B
2	2 Sensor cable, 10-32 pos. to BNC pos.				1761B
3	3 Power supply/signal conditioner				51
4 Output cable, BNC pos. to BNC pos.			1511		
	1	2	3	4	Readout (not supplied)